



KBD-NSC-100

Article number: 74746

Network System Controller with 3-Axis Joystick and Jog Shuttle

Mainfeatures

Hybrid remote keyboard (IP & analog devices)

Programmable presets, tours, patterns and others

Function mapping (up to 8 functions)

Built-in 2 lines character LCD display

2x USB 2.0 interface

Macro function (up to 100 macros)

Separable joystick for left&right-handed operators

Easy firmware upgrade by USB and network

Two-way audio communication

RS-485: 2x half-duplex communication (PTZ & DVR)

Specifications

Control	DIR series, DLR series, DMR series, DPR series, DTR series
Jog shuttle	yes
Joystick	3-axis proportional joystick for manual control of variable speed
Password protection	administrator & users
Macro function	up to 100. 4 function keys can be used as a macro shortcut.
Menu languages	German, English, French, Spanish, Italian, Dutch, Polish, Portugese, Hungarian, Czech, Russian
Ethernet interface	100Base-TX
Audio inputs	1 (Microphone)
Audio output	1x Loudspeaker (mono/stereo, 3.5mm jack)
Serial interfaces	RS-485, RS-232, 10/100-Base-TX, RJ-45
Serial interfaces protocols	Fastrax IIE, Fastrax, Pelco D, Bosch, Honeywell, Samsung

KBD-NSC-100

Continued Specifications

Dimensions (HxWxD)	95x377x177.6mm
Colour	black
Weight	1.1kg
Power consumption	4.5W
Supply voltage	Power Supply Unit included
Certificates	FCC
Parts supplied	Power supply unit with power cord, Joystick connecting cable, Adaptor and accessory pack, INIT CD, Manual
Remarks	Dxx DVR setup via USB mouse which is connected at KBD
Firmware update	firmware upgrade (via USB and network), LCD setup, Remote setup (via PC).
Categorie	Input devices

Your Contact Person



eneo is a registered trademark of
VIDEOR E. Hartig GmbH
Carl-Zeiss-Straße 8
63322 Rödermark
Deutschland
Tel.: +49 6074-888-333
E-Mail: info@eneo-security.com
Web: www.eneo-security.com